

# CE12-4 and CE16S extension boards

## Product description

CE12-4 and CE16S extension boards makes it possible to expand the capacity of the inputs/outputs of an SA3 concentrator or an SA2 controller.

### Extension boards compatible with SA3 card

**12-4 Board**

**RS485 BUS:** SYT1AI cable blinded/pairs 5/10 or 6/10



**Power supply:** SYT 9/10 cable (if remote - Max. 50 m)

**12 Inputs:** SYT 5/10 cable or 6/10 foiled

**4 Outputs:** SYT cable foiled

**16S Board**

**RS485 BUS:** SYT1AI cable blinded/pairs 5/10 or 6/10



**Power supply:** SYT 9/10 cable (if remote - Max. 50 m)

**16 Inputs:** SYT foiled cable (lection adapted to equipment)

### Extension boards compatible with SA2 card

**12-4 Board**

**RS485 BUS:** SYT1AI cable blinded/pairs 5/10 or 6/10



**Power supply:** SYT 9/10 cable (if remote - Max. 50 m)

**Inputs:** SYT 5/10 cable or 6/10 foiled.

**Outputs:** SYT cable foiled. (Section adapted to equipment)

**16S Board**

**RS485 BUS:** SYT1AI cable blinded/pairs 5/10 or 6/10



**Power supply:** SYT 9/10 cable (if remote - Max. 50 m)


**Outputs:** SYT cable foiled. (Section adapted to equipment)

## Advantages


- **Update from ALWIN software:** the procedure for updating the boards can be done directly from the software without moving to the location of the boards.
- **Encrypted communication:** all communication between boards and other equipment is encrypted and secured in accordance with ANSSI requirements. A encoder wheel replaces the DIP Switches and allows the communication of several boards on the same RS485 bus.
- **Optimized use:** equipped with split side panels, boards can be inserted vertically in DIN racks or horizontally in boxes without side panels.
- **Energy saving:** the boards were built with a very low power consumption processor, with optimized inputs.

## Architecture

### Board architecture with SA3



## Board architecture with SA2



## References

REFERENCES	DEFINITION
<b>01-01-0200</b>	CE12/4 extension board for automate SA2: allowing the management of 12 balanced inputs and 4 additional binary outputs
<b>01-01-0211</b>	CE16S extension board for automate SA2: allowing the management of 16 additional binary outputs
<b>01-01-0201</b>	CE12/4 extension board for concentrator SA3: allowing the management of 12 balanced inputs and 4 additional binary outputs
<b>01-01-0212</b>	CE16S extension board for automate SA3: allowing the management of 16 additional binary outputs
<b>01-02-0030-KIT</b>	Din RAIL adapter kit for 1 CE12/4 or 16S board

## Specifications

	CE FOR SA2 ACCESS CONTROLLER		CE FOR SA3 ACCESS CONTROLLER	
	CE12-4	CE16S	CE12-4	CE16S
<b>Number of inputs</b>	12	0	12	0
<b>Number of outputs</b>	4	16	4	16
<b>Input type</b>	Binary or balanced	-	Binary or multi-state (6 states)	-
<b>Output type</b>	Binary		TOR	
<b>Auxiliary input</b>	1 binary inputs for surveillance box	1 binary inputs for surveillance box 1 binary input low voltage	1 binary inputs for surveillance box 1 binary input low voltage	
<b>BUS speed</b>	9 600 or 56 000 bds		Configurable 9600, 19 200,38,400,115,200 bits/s	
<b>Physical interface</b>	RS485, 2 fils			
<b>Cable type</b>	SYT1 A pair-shielded			
<b>Connectors</b>	Screw terminal block	Unpluggable screw terminal block		
<b>Supply voltage</b>	12 to 14,5 V		11 to 15 V	
<b>Power consumption min – max</b>	50Ma -370 mA	46 mA – 460 mA	33 mA- 150 mA	10 mA-400 mA
<b>Power consumption input</b>	20 mA max	-	1 mA max.	-
<b>Consumption / output</b>	20 mA in dry contact	26 mA max by affixed relay	26 mA max. in affixed relay	25 mA max. by affixed relay
<b>General protection</b>	Fuse, 2 A			
<b>Operation</b>	From 0 to 50 °C		From -25° to 65 °C	
<b>Humidity</b>	From 0 to 95% without condensation		From 5 to 85% without condensation	
<b>Storage</b>	From -40 to 70°C		From -40 to 85°C	
<b>Card-only dimensions</b>	155x97 mm		155x97 mm	
<b>Dimensions with breakable edges</b>	-	-	155x106 mm	